



## Electrosurgical Analyzer for function tests of HF Surgical Equipment

- menu guided cursor operation or PC-operation
- HF - power measurement
- HF - voltage measurement
- HF - current measurement
- HF - leakage current measurement
- test load resistances 10 Ohm, 25 – 6375 Ohm in steps of 25 Ohm
- 6 selectable pre resistance
- user specific language setting
- option - suit case



# Technical Data

---

Line voltage:	83 – 264 V ac, 50 /60 Hz	Measurement range	error
Power consumption:	50 VA	HF output power:	0 – 500 W ± 1 W or ± 2,5 % of value
Class:	1	HF leakage current::	0 – 250 mA ± 2 mA ± 5 % of value
Environmental temperature:	+ 5 - + 40°C	Load resistors:	10 Ohm, 25 – 6375 Ohm ± 5 %
Storage temperature:	- 10 - + 50°C	Keyboard:	6 key foil keyboard
Measuring ranges:		Display:	4 x 20 char LCD B/W display
HF-current RMS:	0 - 5000 mA	Interfaces:	1 x USB for PC interface 1 x RS-232 for PC interface 1 x RS-232 for additional test devices
HF-current Peak:	0 - 5000 mA	Testing plugs:	2 x safety plugs 4 mm for HF power 2 x safety plugs 4 mm for HF leakage current 1 x safety plug 4 mm for PE 1 x potential balance
Discrimination:	0,1 mA	Accessories:	1 x potential balance cable 1 x RS-232 interface cable
HF- output power RMS: (in dependence of RL	1 – 500 Watt	Mechanical data:	light way metal case IP20
Crest Faktor: (V2)	1 – 10 (bei > 1000 mA)	Dimensions:	340 x 87 x 290 mm (W x H x D)
HF-leakage current:	0 – 250 mA	Weight:	approx. 3,8 kg
Discrimination:	0,1 mA	Selectable languages:	german, english, french, polish spanish, italian, portuguese, turkish
Bandwidth	0,3 – 10 MHz		
Measuring principle:	thermal electric converter		
Load resistors:	10 Ohm 25 Ohm – 6375 Ohm In steps of 25 Ohm		
Swing in time:	< 3 sec		
Output power:	500 W: 1 min on, 5 min off permanent: max. 200 W at 25°C environmental temperature		

---

## Description of functions:

HF-400 serves to test the function of HF Surgical Equipment. In accordance to the instructions of the manufacturer of such surgical devices, the user can measure the HF output power and the HF leakage current given on a load resistor. The load resistor is adjustable to 10 Ohm and from 25 – 6375 Ohm in steps of 25 Ohm. The test parameters for testing can laid down in a test instruction and can be tested automatically with a PC. This makes it possible to reduce the time for testing. In the use as multi functional test device the measured values were displayed directly. For example:

HF output power  
HF leakage current  
HF current, RMS  
HF voltage, RMS

## HF output power:

During the measurement of power, firstly the software sets the prescribed load resistance to 10 Ohm or from 25 Ohm to 6375 Ohm in 25 Ohm steps. Than the HF output power can be send to the HF-400 and is measured. An automatic range switcher takes care of the optimal control of the RMS-converter. The RMS converter based on a thermal conversion principle and, together with the driver module, is designed for frequencies up to 10 MHz.

## HF leakage current:

The high-frequency leakage current is measured through a 200 Ohm load resistor. During this test load resistor is adjustable.

(The specified measuring accuracy refers to the measuring element. Technical modifications and errors reserved. 02/2013)

---